

Chemical Science

Accepted Manuscript



This is an *Accepted Manuscript*, which has been through the Royal Society of Chemistry peer review process and has been accepted for publication.

Accepted Manuscripts are published online shortly after acceptance, before technical editing, formatting and proof reading. Using this free service, authors can make their results available to the community, in citable form, before we publish the edited article. We will replace this *Accepted Manuscript* with the edited and formatted *Advance Article* as soon as it is available.

You can find more information about *Accepted Manuscripts* in the [Information for Authors](#).

Please note that technical editing may introduce minor changes to the text and/or graphics, which may alter content. The journal's standard [Terms & Conditions](#) and the [Ethical guidelines](#) still apply. In no event shall the Royal Society of Chemistry be held responsible for any errors or omissions in this *Accepted Manuscript* or any consequences arising from the use of any information it contains.



A RET-Supported Logic Gate Combinatorial Library to Enable Modeling and Implementation of Intelligent Logic Functions

Ru-Ru Gao, Shuo Shi*, Ying Zhu, Hai-Liang Huang, and Tian-Ming Yao*^[a]

Received 00th January 20xx,
Accepted 00th January 20xx

DOI: 10.1039/x0xx00000x

www.rsc.org/

ABSTRACT: Boolean logic gates integrate multiple digital inputs into a digital output. Among these, logic gates based on nucleic acids have attracted a great deal of attention due to the perspectives of controlling living systems in the way we control electronic computers. Herein, by employing Thioflavin T (ThT) as signal transducers, we integrated multiple components based on RET into a logic gate combinatorial library, including basic logic gates (NOR, INHIBIT, IMPLICATION), single three-input NOR gate, combinatorial gates (INHIBIT-OR, NOT-AND-NOR). In this library, gates were connected in series where the output of the previous gate was the input for the next gate. Subsequently, by taking advantage of the library, some intelligent logic functions were realized. Expectedly, a biocomputing keypad-lock security system was designed by sequential logic operations. Moreover, a parity checker which can identify even numbers and odd numbers from natural numbers was established successfully. This work helps elucidate the design rules by which simple logic can be harnessed to produce diverse and complex calculations by rewiring communication between different gates. Together, our system may serve as a promising proof of principle that demonstrates increased computational complexity by linking multiple logic gates together.

Introduction

Molecular logic is a continuously developing multidisciplinary field that is driven by the beguiling idea of processing information with the help of molecules and their inherent chemical transformations, showing great potential in many life science applications, such as biomarker detection,¹ disease diagnostics and therapy,² controlling biological progress,³ and promoting the cognition of life phenomena for humans.⁴ Since the first molecular AND function was introduced,⁵ a variety of molecular logic gates have been demonstrated, which primarily focus on the basic logic functions, AND, OR, INHIBIT and XOR.⁶ Nevertheless, the individual control of each logic component in the circuit is difficult. To fulfill the requirements of increased computational complexity, a molecular platform capable of performing multiple logic operations is in high demand. As a consequence, molecular logic relies heavily on functional integration, rather than on physical integration of logic gates as is common for current silicon technology. A few examples demonstrate integration (cascading) of logic gates with molecular components.⁷ Indeed, complex digital computational processes show great dependency on series of simple logic operations, from which sophisticated algorithms can be effectively produced. Consequently, molecular logic has reached the stage where larger circuits execute arithmetic calculations to perform quite complex

tasks, as exemplified by multiplexer/demultiplexer,⁸ flip-flop logics,⁹ encoders/decoders,¹⁰ subtractor/adder,^{6a,11} keypad-lock systems,¹² or even play "tic-tac-toe",¹³ where preloaded multiwall plates were used for game-playing based on molecular logic with DNA strands.

Despite these advancements, a significant challenge in the development of molecular devices for information processing has been the integration of individual logic gates into a complex logic network to emulate the multi-channel capabilities of the silicon computer. Although enzymatic networks with hierarchical circuit design,¹⁴ as well as modular DNA-based Boolean logic gates wired into a three-level circuit have been reported,¹⁵ most logic gates base on DNA replacement,^{6d,16} or employ silver nanoparticles as their fluorescent outputs.¹⁷ The main obstacle for the concatenation of several such logic gates are as follows: 1) These logic operations prove cumbersome for further linking of different logic gates and their integration with electronic devices, and the reaction conditions are very harsh; 2) Their fluorescent signals are unstable, which makes it very difficult to interconnect the gates into a complex circuit; 3) Most basic logic gates utilize different chemical species as input and produce an even broader range of outputs.


In order to design multi-level logic gates and further close the gap between DNA computation and electrical circuitries, herein we have constructed a label-free logic gate library focused on RET which is one type of proto-oncogene and encodes a receptor-type tyrosine kinase that has been implicated in the development of several human cancers, especially thyroid cancer.¹⁸ The logic gate library was implemented for the first time according to DNA hybridization and interaction between small molecules

Shanghai Key Laboratory of Chemical Assessment and Sustainability, Department of Chemistry, Tongji University, Shanghai, 200092 (P.R. China)
E-mail: shishuo@tongji.edu.cn; tmyao@tongji.edu.cn

† Electronic supplementary information (ESI) available. See DOI: 10.1039/x0xx00000x

Chemical Science

ARTICLE



Scheme 1. Schematic interactions of the RET-supported logic library with six basic gates inside. ① The first NOR gate indicated by purple arrows employed RET as the initial state and silver deposition, H^+ as inputs; ② the second INHIBIT gate indicated by grey arrows employed silver deposited RET as the initial state and H^+ , cysteine as inputs; ③ the third INHIBIT gate indicated by pink arrows employed silver deposited RET as the initial state and cysteine; ④ H_2O_2 as inputs; the fourth IMPLICATION gate indicated by green arrows employed RET as the initial state and H^+ , L-DNA as inputs; ⑤ the fifth IMPLICATION gate indicated by blue arrows employed dsDNA as the initial state and silver deposition, cysteine as inputs; ⑥ the sixth IMPLICATION gate indicated by yellow arrows employed silver deposited dsDNA as the initial state and cysteine, H_2O_2 as inputs.

only without DNA replacement (Scheme 1). We proposed the construction of basic logic gates, single three-input, and the cascade

of several chemical logic gates. Interestingly, a keypad-lock security system was designed by sequential logic operations. Moreover, a

logic gate system for identification of even numbers and odd numbers from natural numbers was established successfully by employing four common and simple molecules. First of all, the developed logic gate is label-free realized with short oligonucleotides. Secondly, our methods may minimize or even eliminate complex analysis procedures that involve expensive instrumentation, and hold great promise for low-volume, and rapid readout of the analyte. Thirdly, a fluorescent signal as an output is considered to have a multitude of practical applications since the signal enables easy remote reading with low cost. Last but not the least, the developed system can also perform intelligent logic functions.

RESULTS AND DISCUSSION

Thioflavin T (ThT) consists of a pair of benzothiazole and dimethylaminobenzene rings freely rotating around a C–C bond which is a conjugated π bond between the two moieties.¹⁹ The fluorescence of ThT is quenched due to the internal rotation leading to a twist internal charge transfer (TICT). ThT requires an interaction with a “host” molecule in order to prevent the twisting which renders its fluorescence.²⁰ For the RET sequence, a fitting cavity is available in a flexible hairpin structure at a neutral pH value.²¹ The interaction of the intercalated ThT with the cavities of the sequence is the stabilizing force for ThT binding, decreasing the TICT state, and increasing the fluorescence intensity (Figure 1).²² Focusing on the fluorescence of ThT as the output and normalizing the obtained fluorescence signals by performing a ratio, we converted to Boolean logic levels by imposing a threshold of 0.54, thus constructed various logic gates as described next.

Construction of basic logic gates

NOR and NAND gates are unique because they are functionally complete. That is, any computational operation can be implemented by layering either of these gates alone. Of these, the NOR gate is the simplest to implement using existing genetic parts.²³ A NOR gate is “on” only when both inputs are “off”.²⁴ Based on the above results, we firstly designed a NOR logic gate that employed silver deposition and H^+ as inputs which were added to the solution of RET, and the fluorescence of ThT as the output (Figure 2). With respect to the inputs, the presence and absence of silver deposition and H^+ were defined as “1” and “0” respectively, with a threshold value of 0.54. Upon addition of H^+ , the RET sequence folded into an i-motif structure,^{22a} which couldn't be inserted by ThT. And the fluorescence of ThT turned off (output=0). In addition, silver deposition on DNA scaffolds could effectively block the binding of the ThT to the RET sequence, and also likely worked as a fluorescence quencher, thus the fluorescence was weak in the presence of both inputs. Furthermore, it is interesting to find that the logic system can be reset to its initial states by changing the buffer pH from 5.0 to 7.0 or introducing cysteine with the molar ratio of cysteine/Ag 2.0, which was a crucial property for practical applications of chemical logic gates. The fluorescence curves after resetting are shown in Figure S1.




Figure 1. Fluorescence curves of ThT in aqueous solution (black curve) and ThT intercalated into RET in aqueous solution (red curve).

Moreover, inspired by the Ag–thiols interaction and the phenomenon that the chemisorbed thiols can bind much more strongly than DNA to the silver surface,²⁵ an INHIBIT gate was performed based upon the silver metallized RET by employing H^+ and cysteine as inputs. As shown in Figure 3, a more dramatic fluorescence-on signal was obtained with cysteine (input: 0/1) than with other inputs (0/0, 1/0, 1/1). Thiols can remove the silver deposition from DNA scaffolds via the formation of Ag–S bonds. The “inactive” DNA originally stabilized or protected by silver deposition became “active”, and then ThT had a dramatic increase in fluorescence as a result of the strong interaction between the intercalator (ThT) and the “activated” RET (output=1). These results were in accordance with the proper execution of the boolean INHIBIT logic gate which is represented by the situation where the output is “1” only if one particular input is “1” and the others are “0”. The gate can be easily reset by changing the buffer pH from 5.0 to 7.0 or silver deposition again (Figure S2). Similarly, enlightened by the fact that H_2O_2 can oxidize cysteine to cystine,²⁶ another INHIBIT gate was constructed based upon the silver metallized DNA system via introduction of the two inputs: cysteine




Figure 2. The “NOR” logic gate. (A) Diagram of the operational design of the “NOR” gate with employing RET as the initial state and silver deposition, H^+ as inputs; (B) Fluorescence curves of the NOR gate with different combinations of the inputs; (C) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (D) Electronic equivalent circuitry; (E) Truth table of the NOR gate.




Figure 3. The "INHIBIT" logic gate. (A) Diagram of the operational design of the "INHIBIT" gate with employing silver deposited RET as the initial state and H⁺, cysteine as inputs; (B) Fluorescence curves of the INHIBIT gate with different combinations of the inputs; (C) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (D) Electronic equivalent circuitry; (E) Truth table of the INHIBIT gate.

and H₂O₂ (Figure S3). Only the addition of cysteine (input=0/1) caused fluorescence to increase greatly because the silver metalized RET could be readily released due to the etching interaction between thiols and silver. However, in the presence of both inputs, the oxidation of cysteine by H₂O₂ yields cysteine which can't remove the silver deposition from DNA scaffolds, resulting in fluorescent quenching.

In fact, every elementary logic gate, such as AND, OR, NOR, INHIBIT, can be rewritten by combinations of IMPLICATION (IMP) and FALSE gates.^{11b} Thus, IMP provides an outstanding attribute in Boolean logic. In this study, we constructed an IMP logic gate based upon the DNA/i-motif-mediated fluorescence changes.




Figure 4. The "IMPLICATION" logic gate. (A) Diagram of the operational design of the "IMPLICATION" gate with employing RET as the initial state and H⁺, L-DNA as inputs; (B) Fluorescence curves of the IMPLICATION gate with different combinations of the inputs; (C) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (D) Truth table of the IMPLICATION gate; (E) Electronic equivalent circuitry.

We defined H⁺ and the L-DNA as the two inputs for our logic operation. RET can hybridize with L-DNA to form a DNA duplex with an extra four bases. The formation of DNA duplexes (input: 0/1) led to the significant fluorescence enhancement because ThT was almost non-fluorescent in aqueous solution but showed intense fluorescence upon interaction with the double-stranded DNA by intercalation (output=1). When the RET solution was subjected to the two inputs together, there was competitive formation of dsDNA and i-motif. As shown in Figure 4, the strong fluorescence intensity indicated that the affinity of the double helix was much stronger than that of i-motif. This input/output behavior yielded in an IMPLICATION logic gate: the Boolean function provides the output "1" in all circumstances, except the case one particular input is "1". In addition, Exo III can catalyze the stepwise hydrolysis of mononucleotides from the blunt or recessed 3'-terminus of dsDNA. Its activity on single-stranded DNA (ssDNA) and the 3'-protruding end of dsDNA is limited.²⁷ Therefore, this distinctive Exo III-catalyzed hydrolysis reaction is exploited to make the system feasible to reset. The fluorescence curves after resetting with different combinations of the inputs are presented in Figure S4. Meanwhile, another IMPLICATION gate was realized based on the fact that Graphene Oxide (GO) can differentiate ssDNA and dsDNA due to their characteristic interactions with GO²⁸ (Figure S5). When the RET solution was incubated with GO, due to the π-π stacking effect between single strand DNA and the GO, RET was easily absorbed on the GO and the fluorescence of ThT turned off (output=0). After formation of double stranded DNA (dsDNA), the dsDNA were removed from the GO owing to the weak affinity between GO and dsDNA and the fluorescence recovered (output=1).

It is important to note that dsDNA can also form stable complexes with Ag(I) by inserting the ions inside the double helix, silver nanowires on DNA scaffolds have been constructed through reduction of silver ions-laden λ-DNA.²⁹ Similarly, thiols exhibit intriguing reactivity with the silver deposition. Therefore, the third IMPLICATION logic gate was achieved by taking dsDNA as substrate and utilizing silver deposition and cysteine as inputs (Figure S6). The last basic gate was realized based on the silver deposited DNA duplex by employing cysteine and H₂O₂ as inputs (Figure S7). The true output "1" was obtained only when cysteine was introduced and the input state was (1/0), while the other input states (0/0, 0/1, 1/1) generated the false output "0".

Construction of single three-input NOR gate

A three-input majority gate is one of the most basic logic gates and has been demonstrated in many fields.³⁰ With multiple inputs this gate can accept and produce a high volume of information; thus, on the molecular level a three-input majority gate can serve as a basic and versatile building block for constructing more complex circuits. For a single three-input NOR gate, it possess three inputs and produces an output of 1 only in the absence of any input. In this work we experimentally realized a three-input majority gate based on RET and demonstrated that it reliably produced all the false output "0" with different combinations of the inputs. H⁺, silver deposition and GO were selected as inputs respectively, with a




Figure 5. The single three-input NOR gate. (A) Diagram of the operational design of the single three-input NOR gate with employing RET as the initial state and H⁺, silver deposition, GO as inputs; (B) Fluorescence curves of the three-input NOR gate with different combinations of the inputs; (C) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (D) Electronic equivalent circuitry; (E) Truth table of the NOR gate.

threshold value of 0.54. As shown in Figure 5, the truth table specifies that the three inputs have the same priority among one another. Only when the input state was (0/0/0), the output was “1”, while the other input states (1/0/0, 0/1/0, 1/1/0, 0/0/1, 1/0/1, 0/1/1, 1/1/1) displayed output “0”. These results are in accordance with the proper execution of the NOR logic gate.

Construction of cascaded logic gates

The aforementioned examples have shown the logic library based on RET is composed of several types of logic operations based on two or three simple inputs. However, the major challenge in the logic systems is the possibility of assembling multicomponent/multifunctional logic circuitries. To demonstrate




Figure 6. The three-input combinational gate (INHIBIT-OR). (A) Diagram of the operational design of the single three-input INHIBIT-OR gate with employing silver deposited RET as the initial state and cysteine, H₂O₂, L-DNA as inputs; (B) Fluorescence curves of the INHIBIT-OR gate with different combinations of the inputs; (C) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (D) Electronic equivalent circuitry; (E) Truth table of the combinational gate.




Figure 7. The three-input combinational gate (NOT-AND-NOR). (A) Diagram of the operational design of the single three-input NOT-AND-NOR gate with employing RET as the initial state and T-DNA, silver deposition, GO as inputs; (B) Fluorescence curves of the NOT-AND-NOR gate with different combinations of the inputs; (C) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (D) Electronic equivalent circuitry; (E) Truth table of the combinational gate.

the system necessary for the multi-level integrated circuits, the versatility of inputs is implemented to construct cascaded logic gates. In the following set of representative experiments, we expected our logic system could be scaled up to perform large networking systems mimicking natural biochemical pathways. The first cascaded gate was constructed by combining an INHIBIT gate with an OR gate (Figure 6) Based upon the silver metallized RET system, we chose cysteine, H₂O₂, L-DNA as input 1, input 2 and input 3 respectively in the operation of the combinational gate. When the input states were (0/0/0, 0/1/0, 1/1/0), the output was “0”, while the other input states (1/0/0, 0/0/1, 1/0/1, 0/1/1, 1/1/1) displayed output “1”. Furthermore, the logic system can be reset to its initial states by introducing Exo III or silver deposition again (Figure S8). Another combinational NOT-AND-NOR gate was achieved by utilizing T-DNA, GO and silver deposition as the inputs and the RET solution as the basic system. As shown in Figure 7, when the input states were (0/1/0, 0/0/1, 1/0/1, 0/1/1, 1/1/1), the output was “0”, while the other input states (0/0/0, 1/0/0, 1/1/0) displayed output “1”.

Construction of a superimposed molecular keypad-lock security system

The logic functions described thus far are mainly combinational functions, where the state of the output is determined solely by the input combination, with no dependence on the order in which the inputs are applied. In sequential logic, the most important feature of the keypad-lock security system is the dependence of the output signal not only on the proper combination of the inputs but also on the order in which these inputs are introduced. In other words, one needs to know the exact password that opens this lock. Fundamental logic gates are the basic building blocks for the construction of superior biocomputing security systems. Based on the above discussions, a superimposed molecular keypad-lock security system was constructed. Mixture of RET and ThT was used




Figure 8. The keypad lock with reset function. (A) Diagram of the operational design of the keypad lock with employing RET as the initial state and silver deposition, T-DNA as inputs; (B) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (C) Fluorescence curves of the keypad lock; (D) Truth table of the keypad lock.

as an initial system which involved stepwise treatment with silver deposition and T-DNA defined as input signals. Particularly, T-DNA can hybridize with RET to form a DNA duplex with an extra five bases. The high and weak fluorescence values were considered as 1 ("On") and 0 ("Off"), respectively, with a threshold value of 0.54. Figure 8C shows a bar presentation of the output of the keypad lock. Only the (Ag/T-DNA) input can trigger the system to adopt the "On" state.

To visualize these sequence-dependent phenomena directly, the sequential logic operation with memory function can be constructed as a password entry. As illustrated in Figure 9, the input of Ag was designated as the character "Y" and the input of T-DNA was designated as the character "E". When the input "Y" was added first, emission as the character "S" (strong fluorescence, On) was observed as the result of memorizing the input sequence. The combination of inputs gave the password "YES" to open the keypad lock. On inverting the addition sequence to T-DNA and Ag, an obvious fluorescence quenching (OFF, designated as the character "O") was observed. This input sequence gave the word "EYO", which corresponded to the denial of unauthorized access and failure to open the keypad lock. This demonstrated that one can use "YES" as a security code to open the keypad lock. Use of numerical




Figure 9. Fluorescent keypad to access a secret code with different input sequences.

digits (0–9) as PIN numbers in a two-digit password allows a total of 90 kinds of combination. The choice becomes wider (650 different combinations) when individual letters (A–Z), each signifying a specific ionic input, are used as PIN numbers. Thus, access codes would be made possible by assigning the correct starting (Ag) and ending (T-DNA) inputs to two specific letters (Y and E, respectively) and different inputs to all of the other letters, to ensure that only one code would work. But there are many combinations to try and this adds to the complexity of cracking the keypad lock.

The developed keypad lock can be facily reset after operations, which is critical for multiple operations of the keypad lock. Otherwise, the function could be performed only once, which would limit the effectiveness of such strategies. If one inputs the correct password, the lock will be opened and cannot be closed again. In contrast to previous studies, this RET-based system could be regenerated. Here, by taking advantage of the attractive properties of Ag–thiols interaction and Exo III, the designed keypad system can be facily reset from the "ON" or the "OFF" state without a laborious process. As shown in Figure 8A, the DNA duplexes have a blunt 3'-terminus and a five-base adenine tail. Since Exo III can only catalyze the hydrolysis of mononucleotides from the blunt 3'-terminus of dsDNA, addition of Exo III would start the stepwise removal of mononucleotides from the blunt 3'-terminus of T-DNA, with RET remaining intact. Followed by the hydrolysis process, the solution is heated for 5 min to inhibit the activity of Exo III so as to eliminate the interference from Exo III. Figure 10 shows that after resetting the system, the ON or the OFF state could be reached again when the system was triggered by the different input sequences. This demonstrated that the logic operation reported here can be used for the next cycle, which is a crucial property for the practical application of keypad locks.




Figure 10. Fluorescence curves of the system after resetting with different combinations of the inputs for the keypad lock.

Construction of the parity checker

A multifunctional molecular platform should be capable of performing a multitude of logic operations. One of these is the function of a parity checker, an essential device in the detection of erroneous procedures in data transmission.³¹ To demonstrate the application prospect of the RET-regulated logic platform, we have applied this circuit with slight modification to identify even numbers and odd numbers from natural numbers less than 10. Firstly, these decimal numbers were encoded with binary-coded decimal (BCD) code.³² Each decimal digit was transformed into a four-bit binary number, then GO, H⁺, Exo III, cysteine were chosen to assign to the four bits as the inputs, respectively and the silver metalized dsDNA was used as the initial state. When the input state is (0/0/0/1), the silver metalized dsDNA could be readily released owing to the specific thiols–Ag interaction (output=1). Exo III can catalyze the stepwise hydrolysis of dsDNA to form ssDNA, and hence the (0/0/1/1) state presented a true output. Remarkably, when the inputs involved H⁺, Exo III, cysteine, H⁺ inactivated Exo III and the input state (0/1/1/1) also presented a true output. According to the experimental results, H⁺ and GO had little influence on dsDNA, while much influence on ssDNA. As we had expected, the input states (0/1/0/1, 1/0/0/1) resulted in true outputs and the input state (0/1/0/0) resulted in a false output. The other input states involved silver deposition all presented false outputs. The computational results of the four-input binary logic gate system are shown in Figure 11. The checker gave an alert in form of a binary “1” for the output if it received an odd number. As expected, the corresponding fluorescence intensity of all the odd numbers produced a true output, while the even numbers presented a false output. The checker gave a binary output “0” for all the even numbers. These results demonstrated the parity checker is capable of identification of all the even numbers and odd numbers because the parity of a natural number is determined by the digit in the units position, no matter how large the number is.

Perspectives for medical applications

Moreover, our molecular logics could potentially be applied to medical diagnostics. For example, in the previously described INHIBIT gates which employed silver deposited DNA as initial states, cysteine and H₂O₂ performed simple logic operation. Cysteine plays a vital role in reversible redox reactions inside cells, which have numerous biological functions in metabolism and detoxification. It is also recognized to be a potential neurotoxin and serves as a biomarker for various medical diagnosis. For instance, cysteine at a deficient level is associated with slowed growth, hair depigmentation, edema, liver damage, skin lesions, and weakness.³³ A facile analysis of cysteine level is therefore pivotal to the early diagnosis of these diseases. Silver nanoclusters (AgNCs) have been recently used to construct optical sensors for cysteine due to the good biocompatibility and photostability.³⁴ When AgNCs were exposed to the targeted cysteine, the turn-off changes in fluorescence intensity of the assay solution provided superior




Figure 11. The logic gate system for identification of even numbers and odd numbers from natural numbers less than 10 with employing silver deposited dsDNA as the initial state. (A) Diagram of the operational design of the parity checker; (B) Fluorescence curves of the different input states; (C) Column diagram of the fluorescence intensities: The red dashed line shows the threshold (0.54); (D) Truth table of the parity checker.

selectivity for cysteine owing to the specific thiols–Ag interaction. Similarly, our silver deposited DNA has the potential to respond to cysteine inside cells. What's more, by employing ThT as fluorescence indicator, it is expected to perform a binding-induced fluorescence turn-on assay instead of turn-off changes which are often suspected to be false positive results. Addition of H₂O₂, another input of the INHIBIT gates, is further proof for cysteine analysis. These demonstrate the feasibility of performing medical diagnostics using a logic gate design. Further work in our group along this line is expected to realize the idea.

CONCLUSION

In conclusion, we have successfully established a versatile, alternate, large-scale logic library based on DNA hybridization and reaction between small molecules only, with a final fluorescent signal output for logic performance and detection. In this logic gate library, the output of the previous gate was used by the next logic gate. By means of this concatenation, all the basic logic gates were connected to communicate with each other. In addition, we demonstrated that a library of simple gates can be used to form more complex computational operations by linking the gates using diffusible chemical signals. The multi-level logic gates (INHIBIT–OR,

NOT-AND-NOR) showed a high switching ratio between output signals "1" and "0", which makes it possible to distinguish different health statuses and facilitates fast and accurate diagnosis at the same time. Subsequently, a biocomputing keypad-lock security system was designed by sequential logic operations. Moreover, a parity checker which can identify even numbers and odd numbers from natural numbers was established successfully. The distinctive advantage of this system was label-free, which made it simple to operate. Importantly, these logic gates were carried out in aqueous media, potentiating its applications in biological and biomedical systems. Due to its low-cost, well-ordered and predictable structure of our system, our sensor may serve as a promising proof of principle that demonstrates increased computational complexity and enhanced sensor performance by linking multiple logic gates together. Further work along these lines is expected to produce such information-processing and smart therapeutic agents.

EXPERIMENTAL DETAILS

Chemicals and materials

DNA sequences used in this work are listed as follows:

RET: 5'-CCCGCCCCCGCCCGCC-3'

L-DNA: 5'-GGGGCGGGGCGGG-3'

T-DNA: 5'-AAAAAGGGCGGGCGGGCGGG-3'

All of the synthesized oligo-nucleotides were purchased from Shanghai Sangon Biotechnology Co. Ltd. (Shanghai, China). Silver nitrate (AgNO_3) and sodium borohydride (NaBH_4) were purchased from Aladdin Ltd. (Shanghai, China). Thioflavin T (ThT) and L-cysteine was obtained from Sigma-Aldrich. Hydrogen peroxide solution (30%) was purchased from Sinopharm Chemical Reagent Co. Ltd. (Shanghai, China). Tris-Ac buffer (10mM, pH=8) was used to control the acidity of the reaction solution. All chemicals used in this work were of analytical reagent and obtained from commercial sources and directly used without additional purification.

Synthesis of silver deposition on ssDNA scaffolds

The ssDNA-templated silver deposition was synthesized by reduction of AgNO_3 with NaBH_4 in the presence of DNA. Briefly, RET (1.0×10^{-4} M, 4 μL) was mixed with excess of AgNO_3 (1.2×10^{-2} M, 4 μL) (120:1 AgNO_3 /DNA molar ratio) in 200 μL buffer (10 mM Tris-Ac, pH=8). After 5 min incubation, a freshly prepared NaBH_4 (3×10^{-2} M, 8 μL) at a 1:5 molar ratio of $[\text{AgNO}_3]/[\text{NaBH}_4]$ was dropped into the above aqueous solution under vigorous stirring. After mixture, the resulting yellow colloidal silver solution was stirred for another 40 min.

Synthesis of silver deposition on dsDNA scaffolds

The method for synthesis of silver deposition on dsDNA scaffolds is similar to silver deposition on ssDNA. Briefly, RET (1.0×10^{-4} M, 4 μL) was first hybridized with its complementary oligonucleotide strand L-DNA/T-DNA at the same concentration (1.0×10^{-4} M, 4 μL) in 200 μL buffer (10 mM Tris-Ac, pH=8) for 30 min. Next, excess of AgNO_3 (1.2×10^{-2} M, 6 μL) at a 120:1 ratio of $[\text{AgNO}_3]/[\text{DNA}]$ was added to

the DNA duplex solutions. After 5 min incubation, a freshly prepared NaBH_4 (3×10^{-2} M, 12 μL) at a 1:5 molar ratio of $[\text{AgNO}_3]/[\text{NaBH}_4]$ was dropped into the above aqueous solution under vigorous stirring. After mixture, the resulting yellow colloidal silver solution was stirred for another 40 min.

The fluorescence assay

Cysteine: Firstly, the above silver-coated ssDNA/dsDNA was mixed with cysteine (1×10^{-3} M, 50 μL). After the mixture equilibrated for 1 h at room temperature, ThT (100 μM , 20 μL) was added and equilibrated for 1 min before spectral measurements.

H_2O_2 : Cysteine was firstly treated with H_2O_2 (120:1 cysteine/ H_2O_2 molar ratio) for 30 min in 10 mM Tris-Ac buffer (pH=8.0), and the resulting solution was then transferred to the silver-coated DNA system. ThT (100 μM , 20 μL) was added and equilibrated for 1 min before spectral measurements.

I-motif: RET (10 μM) was diluted in 970 μL buffer (10 mM Tris-Ac, pH=5). After 5 min incubation, ThT (100 μM , 20 μL) was added and equilibrated for 1 min before spectral measurements.

And after that an aliquot of 0.1 mL mixture were excited at 425 nm, and fluorescence intensity were collected from 445 to 600 nm.

ACKNOWLEDGMENT


This work was financially supported by the National Science of Foundation of China (81171646, 31170776 and 21472139), the Science and Technology Commission of Shanghai Municipality (14DZ2261100) as well as the Fundamental Research Funds for the Central Universities.

REFERENCES

- M. Zhou, N. Zhou, F. Kuralay, J. R. Windmiller, S. Parkhomovsky, G. Valdés - Ramírez, E. Katz and J. Wang, *Angew. Chem. Int. Ed.*, 2012, **51**, 2686-2689.
- M. You, L. Peng, N. Shao, L. Zhang, L. Qiu, C. Cui and W. Tan, *J. Am. Chem. Soc.*, 2014, **136**, 1256-1259.
- Y. Benenson, B. Gil, U. Ben-Dor, R. Adar and E. Shapiro, *Nature*, 2004, **429**, 423-429.
- E. Shapiro and Y. Benenson, *Sci Am.*, 2007, **17**, 40-47.
- P. A. de Silva, N. H. Gunaratne and C. P. McCoy, *Nature*, 1993, **364**, 42-44.
- (a) J. Elbaz, F. Wang, F. Remacle and I. Willner, *Nano Lett.*, 2012, **12**, 6049-6054; (b) T. Li, E. Wang and S. Dong, *J. Am. Chem. Soc.*, 2009, **131**, 15082-15083; (c) M. N. Stojanovic, T. E. Mitchell and D. Stefanovic, *J. Am. Chem. Soc.*, 2002, **124**, 3555-3561; (d) F. Wang, X. Liu and I. Willner, *Angew. Chem. Int. Ed.*, 2015, **54**, 1098-1129; (e) R. Orbach, B. Willner and I. Willner, *Chem. Commun.*, 2015, **51**, 4144-4160.
- (a) R. Guliyev, S. Ozturk, Z. Kostereli and E. U. Akkaya, *Angew. Chem.*, 2011, **123**, 10000-10005; (b) T. Gupta and M. E. van der Boom, *Angew. Chem.*, 2008, **120**, 2292-2294; (c) T. Gupta and M. E. van der Boom, *Angew. Chem.*, 2008, **120**, 5402-5406; (d) S. Silvi, E. C. Constable, C. E. Housecroft, J. E. Beves, E. L. Dunphy, M. Tomasulo, F. M. Raymo and A. Credi, *Chem. Eur. J.*, 2009, **15**, 178-185; (e) J. Elbaz, O. Liubashevski, F. Wang, F. Remacle, R. D. Levine and I. Willner, *Nat. Nanotechnol.*, 2010, **5**, 417-422.
- (a) O. AltanBozdemir, *Chem. Sci.*, 2013, **4**, 858-862; (b) M. Amelia, M. Baroncini and A. Credi, *Angew. Chem.*, 2008, **120**,

- 6336-6339; (c) J. Andréasson, S. D. Straight, S. Bandyopadhyay, R. H. Mitchell, T. A. Moore, A. L. Moore and D. Gust, *Angew. Chem. Int. Ed.*, 2007, **46**, 958-961; (d) E. Perez-Inestrosa, J.-M. Montenegro, D. Collado and R. Suau, *Chem. Commun.*, 2008, 1085-1087.
- 9 (a) B.-B. Cui, Y.-W. Zhong and J. Yao, *J. Am. Chem. Soc.*, 2015, **137**, 4058-4061; (b) P. Remón, M. Bälter, S. Li, J. Andréasson and U. Pischel, *J. Am. Chem. Soc.*, 2011, **133**, 20742-20745.
- 10 (a) J. Andréasson, S. D. Straight, T. A. Moore, A. L. Moore and D. Gust, *J. Am. Chem. Soc.*, 2008, **130**, 11122-11128; (b) P. Ceroni, G. Bergamini and V. Balzani, *Angew. Chem.*, 2009, **121**, 8668-8670; (c) Y. He, Y. Chen, C. Li and H. Cui, *Chem. Commun.*, 2014, **50**, 7994-7997.
- 11 (a) O. A. Bozdemir, R. Guliyev, O. Buyukcakir, S. Selcuk, S. Kolemen, G. Gulseren, T. Nalbantoglu, H. Boyaci and E. U. Akkaya, *J. Am. Chem. Soc.*, 2010, **132**, 8029-8036; (b) M. Elstner, J. Axthelm and A. Schiller, *Angew. Chem. Int. Ed.*, 2014, **53**, 7339-7343.
- 12 (a) J. Zhu, X. Yang, L. Zhang, L. Zhang, B. Lou, S. Dong and E. Wang, *Chem. Commun.*, 2013, **49**, 5459-5461; (b) Z. Zhou, Y. Liu and S. Dong, *Chem. Commun.*, 2013, **49**, 3107-3109; (c) C. P. Carvalho, Z. Domínguez, J. P. Da Silva and U. Pischel, *Chem. Commun.*, 2015, **51**, 2698-2701.
- 13 (a) M. N. Stojanovic, *Prog. Nucleic. Acid. Re.*, 2008, **82**, 199-217; (b) J. Macdonald, D. Stefanovic and M. N. Stojanovic, *Sci. Am.*, 2008, **299**, 84-91; (c) J. Macdonald, Y. Li, M. Sutovic, H. Lederman, K. Pendri, W. Lu, B. L. Andrews, D. Stefanovic and M. N. Stojanovic, *Nano Lett.*, 2006, **6**, 2598-2603.
- 14 (a) M. N. Stojanovic and D. Stefanovic, *Nat. Biotechnol.*, 2003, **21**, 1069-1074; (b) E. Katz and S. Minko, *Chem. Commun.*, 2015, **51**, 3493-3500; (c) E. Katz and V. Privman, *Chem. Soc. Rev.*, 2010, **39**, 1835-1857.
- 15 (a) B. M. Frezza, S. L. Cockroft and M. R. Ghadiri, *J. Am. Chem. Soc.*, 2007, **129**, 14875-14879; (b) R. Orbach, S. Lilienthal, M. Klein, R.D. Levine and I. Willner, *Chem. Sci.*, 2015, **6**, 1288-1292.
- 16 (a) L. Qian and E. Winfree, *Science*, 2011, **332**, 1196-1201; (b) L. Qian, E. Winfree and J. Bruck, *Nature*, 2011, **475**, 368-372.
- 17 D. L. Ma, H. Z. He, V. Y. Ma, D. H. Chan, K. H. Leung, H. J. Zhong, L. Lu, J. L. Mergny and C. H. Leung, *Anal. Chim. Acta.*, 2012, **733**, 78-83.
- 18 (a) K. Guo, A. Pourpak, K. Beetz-Rogers, V. Gokhale, D. Sun and L. H. Hurley, *J. Am. Chem. Soc.*, 2007, **129**, 10220-10228;
- (b) J. Zhou, C.-Y. Wei, G.-Q. Jia, X.-L. Wang, Z.-C. Feng, L. Can, *Mol. BioSyst.*, 2010, **6**, 580-586.
- 19 V. Babenko and W. Dzwolak, *Chem. Commun.*, 2011, **47**, 10686-10688.
- 20 R. Ghosh and D. K. Palit, *ChemPhysChem*, 2014, **15**, 4126-4131.
- 21 I. J. Lee, S. P. Patil, K. Fhayli, S. Alsaiani and N. M. Khashab, *Chem. Commun.*, 2015, **51**, 3747-3749.
- 22 (a) V. I. Stsiapura, A. A. Maskevich, S. A. Tikhomirov and O. V. Buganov, *J. Phys. Chem.*, 2010, **114**, 8345-8350; (b) P. K. Singh, M. Kumbhakar, H. Pal and S. Nath, *Phys. Chem. Chem. Phys.*, 2011, **13**, 8008-8014.
- 23 T. W. Scharle, *Notre Dame J. Formal Logic.*, 1965, **6**, 209-217.
- 24 A. Tamsir, J. J. Tabor and C. A. Voigt, *Nature*, 2011, **469**, 212-215.
- 25 Z. Chen, Y. Lin, C. Zhao, J. Ren and X. Qu, *Chem. Commun.*, 2012, **48**, 11428-11430.
- 26 F. Wang, X. Liu, C. H. Lu and I. Willner, *ACS nano*, 2013, **7**, 7278-7286.
- 27 G. Strack, M. Ornatska, M. Pita and E. Katz, *J. Am. Chem. Soc.*, 2008, **130**, 4234-4235.
- 28 H. Jang, Y. K. Kim, H. M. Kwon, W. S. Yeo, D. E. Kim and D. H. Min, *Angew. Chem.*, 2010, **122**, 5839-5843.
- 29 (a) E. Braun, Y. Eichen, U. Sivan and G. Ben-Yoseph, *Nature*, 1998, **391**, 775-778; (b) L. Berti, A. Alessandrini and P. Facci, *J. Am. Chem. Soc.*, 2005, **127**, 11216-11217.
- 30 (a) A. Imre, G. Csaba, L. Ji, A. Orlov, G. Bernstein and W. Porod, *Science*, 2006, **311**, 205-208; (b) W. Tang, S.-C. Hu, H.-M. Wang, Y. Zhao, N. Li, and F. Liu, *Chem. Commun.* 2014, **50**, 14352-14355; (c) W. Li, Y. Yang, H. Yan and Y. Liu, *Nano Lett.*, 2013, **13**, 2980-2988.
- 31 M. Pärss, C. C. Hofmann, K. Willinger, P. Bauer, M. Thelakkt and J. Köhler, *Angew. Chem. Int. Ed.*, 2011, **50**, 11405-11408.
- 32 (a) A. Timoshenko, S. Rastogi and P. Lala, *Br. J. cancer.*, 2007, **97**, 1090-1098.
- 33 (a) S. Shahrokhian, *Anal. Chem.*, 2001, **73**, 5972; (b) H. S. Jung, J. H. Han, T. Pradhan, S. Kim, S. W. Lee, J. L. Sessler, T. W. Kim, C. Kang and J. S. Kim, *Biomaterials*, 2012, **33**, 945.
- 34 (a) X. Yuan, Y. Tay, X. Dou, Z. Luo, D. T. Leong and J. Xie, *Anal. Chem.*, 2013, **85**, 1913-1919; (b) Z. Chen, D. Lu, Z. Cai, C. Dong, S. Shang, *Luminescence*, 2014, **29**, 722-727.

TOC



We constructed a logic gate combinatorial library, including basic logic gates, single three-input NOR gate, combinatorial gates to realize intelligent logic functions: keypad lock and parity checker.